



SUTO current clamp sensor is an AC RMS current sensor composed of a flexible active part (Rogowski coil model) connected to a compact digital converter, capable of measuring the current carried on a power conductor up to a value of 3000 A AC.

The digital converter supplies an output of 4-20 mA DC in linear proportion to the measured current.

CURRENT SENSOR APPLICATION

- Current sensing at compressors for load / unload analysis
- Current sensing for power / energy measurement
- Evaluation of machine operation hours

CURRENT SENSOR FEATURES

- Easy installation
- Wide measuring range
- Accurate current sensing
- 4-20 mA output signal



Position sensitivity		
Conductor Position	Typical Error(%)	
	<0.5%	
•	<0.8%	
•	<1%	

CURRENT SENSOR TECHNICAL DATA

General Specifications	S554 0155 / S554 0156	S554 0157 / S554 0158
Measuring range	10 1000 A AC	30 3000 A AC
Fundamental frequency	40 70 Hz	
Output signal	4 20 mA DC 0 A AC = 4 mA DC 1000 A AC = 20 mA DC	4 20 mA DC 0 A AC = 4 mA DC 3000 A AC = 20 mA DC
Maximum output	21,6 mA DC	
Load impedance	≤ 300 Ω	
Accuracy	0.5% of reading + 0.2% of range	
Power supply	10 VDC to 32 VDC	
Current consumption	≤ 30 mA	
Clamp diameter	100 mm (1000 A)	150 mm (3000 A)
Maximum temperature of clamped cable	≤ +80°C	
Protection rating	IP67	_

CURRENT SENSOR ORDERING

Please use the following table to assist in placing your order with our sales staff.



Current Sensor		
Order No.	Description	
S554 0156	SUTO current clamp sensor, 1000 A, 100 mm diameter, including connector to S551	
S554 0155	SUTO current clamp sensor, 1000 A, 100 mm diameter, open wire ends	
S554 0157	SUTO current clamp sensor, 3000 A, 150 mm diameter, including connector to S551	
S554 0158	SUTO current clamp sensor, 3000 A, 150 mm diameter, open wire ends	

EUROPEAN OFFICE	CHINA OFFICE	ASIA / PACIFIC OFFICE
SUTO iTEC GmbH	SUTO iTEC (China) Co. Ltd	SUTO iTEC (ASIA) Co. Limited
Werkstr. 2	D3 Building, Unit A, 11/F,	Room 10, 6/F, Block B, Cambridge Plaza
79426 Buggingen	TCL International E City	188 San Wan Road, Sheung Shui, N.T.
Germany	1001 Zhongshanyuan Road, Nanshan	Hong Kong
Fon: +49(0) 7631 936 889 0	Shenzhen, China	Tel: +852 2328 9782
Fax: +49 (0) 7631 936 889 19	Tel: +86 (0) 755 8619 3164	Fax: +852 2671 3863
Mail: sales@suto-itec.com	Fax: +86 (0) 755 8619 3165	Email: sales@suto-itec.asia
	Email: sales.cn@suto-itec.asia	